

Receiver and Low Power Digital Filter Therefor

Technical Field

5 This invention relates to digital communication technology, and in particular to a filter for correlating known coefficients with a data sequence.

Background of the Invention

10 In a spread spectrum communication system, the transmitted signal is spread over a frequency band that is significantly wider than the minimum bandwidth required to transmit the signal. By spreading transmission bandwidth across a broader bandwidth than minimally required, power levels at any given frequency within the bandwidth are significantly reduced. In one type of spread spectrum communication system, known as a direct sequence code division multiple access (CDMA) modulation system, a radio frequency (RF) carrier is modulated by a known digital code sequence referred to as a spreading code. The spreading
15 code has a bit rate, or chipping rate, that is much higher than a clock rate of the underlying information signal. The RF carrier may be binary or quadrature modulated by one or more data streams. The data streams have one phase when the spreading code represents a data "one" or "high" and a predetermined phase shift (e.g., 180° for binary modulation and 90° for quadrature modulation) when the spreading code represents a data "zero" or "low". These
20 types of modulation techniques are commonly referred to as binary shift key modulation (BPSK) and quadrature shift key modulation (QPSK), respectively.

To retrieve the data encoded in a transmitted signal upon being received as a received signal, CDMA systems despread received signal samples with the same spreading code as was used to encode the data. CDMA systems employ a filter for correlating the spreading
25 code with received signal samples to determine the received signal samples in a multi-chip data sequence.

A low power consuming analog filter for CDMA systems is disclosed in Low-Power Consuming Analog-Type Matched Filter for DS-CDMA Mobile Radio, by M. Sawahashi, F. Adachi, G. Shou, and C. Zhou, published in IEICE Transactions Fundamentals, Vol. E79-A,
30 No. 12, Dec. 1996, pp2071-2077.

In one known matched filter, multi-bit received signal samples are clocked through a delay line comprised of a plurality of delay stages, such as a shift register. The delays in the shift register are of a multiple bit width sufficient to accommodate the received signal samples. Each of the delay stages provides a delay of less than one-half of the period of the spreading code clock, or chipping rate, to satisfy the Nyquist sampling theorem. The signal samples propagate down the delay line through a series of successive shifts at a rate corresponding to the chipping rate. Taps at each delay stage provide the delayed signal samples for multiplication by respective tap weights associated with the respective delay stages to produce product terms, which when summed, provide the filter output. The tap weights represent the spreading code used to encode information on the transmission signal prior to being transmitted. The filter output is a correlation of the received signal samples with the spreading code represented by the tap weights.

Each time a new received signal sample is clocked into the delay line, each stage of the delay line is clocked to shift the previously received signal samples along the delay line by one delay stage. A received signal sample that has shifted completely through the delay line is shifted out of the delay line, as is known in the art. A shortcoming of this straightforward implementation is the amount of power consumed by the delay line due to each stage of the delay line being clocked each time a new received signal sample is introduced into the delay line.

U.S. Patent No. 6,075,807 teaches a digital matched filter for CDMA systems that include a digital delay line having a plurality of successive delay stages adapted to receive a digital signal and propagate the digital signal therethrough at a fixed rate. A correlator is coupled to the delay line to correlate the digital signal to a predefined spreading code to provide a correlation signal representing a degree of correlation of the digital signal to the spreading code. A window logic unit is coupled to the correlator to enable operation of the correlator only during successive discrete time periods of the correlation signal corresponding to a high degree of correlation of the digital signal to the spreading code.

Summary of the Invention

In accordance with the invention or a digital filter or a receiver including a digital filter includes at least two multiple stage shift registers. A plurality of multipliers corresponding in number to the number of stages in the at least two multiple stage shift

registers receive as a first input an output from a corresponding stage of the at least two multiple stage shift registers. A tap weight shifter is coupled to a tap weight source to receive tap weights. The tap weight shifter is coupled to provide a second input to each multiplier. Each multiplier produces an output that is the product of inputs thereto. An adder
5 sums the multiplier outputs to provide a sum output. The tap weight shifter then circularly shifts the tap weights and another multiply-add operation occurs. Several shift/multiply/add cycles may occur before data is again shifted into the at least two multiple stage shift registers, and another multiply-add operation occurs.

10 Brief Description of the Drawing

Figure 1 is a simplified block diagram of a receiver including a digital filter for despread-
ing a received signal in accordance with the present invention;

Figure 2 is a simplified block diagram of a low power digital filter for despread-
ing a received signal in accordance with the present invention that may be employed in the
15 receiver of Figure 1; and

Figure 3 is a simplified block diagram of an alternate embodiment low power digital
filter for despread-
ing a received signal in accordance with the present invention that may be
employed in the receiver of Figure 1; and

Figure 4 is a simplified block diagram of yet another alternate embodiment low
20 power digital filter in accordance with the present invention in which the number of taps is
not a product of two integer numbers.

Detailed Description

Figure 1 represents a receiver 10 employing an illustrative embodiment of the
invention. Receiver 10 may be a handset, a base station, or any receiver employing a
25 matched digital filter. Receiver 10 receives a radio frequency (RF) signal on antenna 20 and
down converts the RF signal to a baseband signal by multiplying the received signal by a
carrier frequency generated by a local oscillator. The down-converted signal is then
converted from an analog signal to a multi-bit digital signal by an analog-to-digital converter
24. The digital signal may be filtered by a low pass filter to remove aliasing noise, resulting
30 in multi-bit received digital signal samples. The received digital signal samples are changed
if necessary to the form of a multi-bit digital signal having a chipping rate of the spreading

code originally used to modulate the digital information of the signal. The received digital signal samples may additionally include two components, an I channel component 26 and a Q channel component 28. The I and Q channel signal components may be processed in a number of functions, such as in a rake receiver 30 including a despreader 34 to demodulate the received digital signal samples, and in a cell search circuit 32 including a despreader 36 to provide synchronized tracking, as are mentioned below. The correlation information produced by the rake receiver and cell search may be further processed such as by processor 42.

An illustrative embodiment of a digital matched filter 60 that can be implemented in software, hardware such as an integrated circuit, or a combination of software or hardware, is shown in Figure 2. The integrated circuit may be, for example, be a macrocell in an application specific integrated circuit, a microprocessor, a microcontroller, or a digital signal processor. Defining T as the number of taps in a straight-forward implementation, as described above, of a digital filter. The T taps are factored into a product of N and L , where $N \times L = T$, and N and L are any integers that divide into T . Matched filter 60 is comprised of $T + N$ multiple bit delays. The use of the N additional delays (as compared to the straight-forward implementation) will become clear below. As will be explained below, the invention can accommodate a number of taps that can not be divided into a product of two integers.

An array 62 of multiple bit delays D_{11} through D_{NL+1} are arranged as an $N \times L+1$ array, or equivalent, illustratively having N rows and $L+1$ columns. In the illustrated embodiment, N is 4 although the invention is not limited thereto. The bit-width of each delay depends on system design, such as the number of bits in the output of analog-to-digital converter 24. Each row of delays in array 62 forms a row shift register 64_1 through 64_N (in the illustrated embodiment, 64_1 through 64_4) connected as shown. Each row shift register, when clocked, shifts or transfers data from the output of each stage to a "downstream" stage for storage therein, as is known in the art. The clocking is not illustrated in Figure 2; one skilled in the art would understand how to clock the delays.

Digital data samples, each representing a sample at a sample instant, received on line 68 are clocked into registers of buffer 66 to provide a parallel output from buffer 66 of N digital signal samples. Buffer 66 is comprised of N registers D_1 through D_N (in the

illustrated embodiment, four registers D_1 through D_4), which in a preferred embodiment are of the same, or greater, bit width as the bit width of delays D_{11} through $D_{N_{L+1}}$. The output of registers D_1 through D_N of buffer 66 are coupled as inputs to respective shift registers 64_1 through 64_N as shown in Figure 2. Each of shift registers 64_1 through 64_N is connected to receive as an input an output from a corresponding register D_1 through D_N of buffer 66. In one embodiment, the digital data samples held in buffer 66 are not accessible to be a multiplier or multiplicand, and while held in buffer 66 do not contribute to an output from multiplier 60.

The output of each multiple bit delay D_{11} through $D_{N_{L+1}}$ is coupled as a multiplicand input to a respective multiplier M_{11} through $M_{N_{L+1}}$ (in the illustrated embodiment, M_{11} through $M_{4_{L+1}}$) as shown. A tap weight coefficient is provided as the multiplier input to each of multipliers M_{11} through $M_{N_{L+1}}$. In a preferred embodiment, the tap weight coefficients are binary and may take on the values of a logic zero or a logic one. Since in the preferred embodiment, the tap weight coefficients are single bits that are either a one or a zero, a multiplication operation *per se* does not occur but rather the tap weight coefficients determine whether the output from a corresponding multiple bit delay contributes to sum 72 or does not contribute to sum 72 produced by adder 70.

In a CDMA application, coefficients C_0 through C_{T-1} are one bit wide tap weights representing the spreading code. However, the invention is not limited to one bit wide tap weights. Furthermore, not all tap weights must be of the same bit width. In non-CDMA applications, coefficients C_0 through C_{T-1} may be of a bit width of greater than one bit, but typically be of a bit width less than or equal to the bit width of delays D_{11} through $D_{N_{L+1}}$, or less than or equal to the bit width of the digital signal samples. In applications where the tap weights are greater than one bit in width, a multiplication may occur to generate the outputs O_{11} through $O_{N_{L+1}}$.

Each multiplier M_{11} through $M_{N_{L+1}}$ produces a corresponding output O_{11} through $O_{N_{L+1}}$ that is the product of the two inputs to each respective multiplier. The outputs O_{11} through $O_{N_{L+1}}$ (in the illustrated embodiment O_{11} through $O_{4_{L+1}}$) from corresponding multipliers M_{11} through $M_{N_{L+1}}$ are provided as inputs to adder 70. Outputs O_{11} through $O_{N_{L+1}}$ are combined by adder 70 to form sum 72, which is the output from adder 70. Sum 72 is the correlation of the spreading code represented by coefficients C_0 through C_{T-1} with

samples of the received signal. The magnitude of the correlation determines whether there is meaningful information to be extracted from the received signal samples. In a CDMA system, the correlation sum is used *inter alia* for synchronization, capture, synchronized tracking, and data demodulation. The correlation sum may be used for other purposes in non-CDMA applications.

Coefficients C_0 through C_{T-1} may be provided by any technique to achieve the inventive digital filter 60. For example, the coefficients C_0 through C_{T-1} may be provided to tap changer 76 from a tap weight source 74, such as but not limited to random access memory (RAM), read only memory (ROM), or a processor.

In operation, digital filter 60 illustrated in Figure 2 receives digital signal samples, for example from an analog-to-digital converter 24, on line 68. The digital signal samples are clocked at the spreading code clock rate into the registers D_1 through D_N of buffer 66. In a preferred embodiment, the digital data samples are individually clocked into registers D_1 through D_4 of buffer 66. For example, a digital signal sample is clocked into register D_4 . The next digital signal sample is clocked into register D_3 . The next digital signal sample is clocked into register D_2 , and the next digital signal sample is clocked into register D_1 . Each register D_1 through D_4 provides at its output the digital signal sample stored therein. Once registers D_1 through D_4 are updated with digital signal samples, the row shift registers are clocked to shift the digital signal samples from the output of registers D_1 through D_4 of buffer 66 into respective delays of the corresponding row shift registers 64_1 , 64_2 , 64_3 , and 64_4 . In this manner, after the row shift registers are clocked $L+1$ times, all of the delays D_{11} through D_{N+1} are filled with valid digital signal samples. As is known in the art, until all of the delays are updated to contain valid digital signal samples, the correlation sum 72 may be discarded. Furthermore, while the buffer of N registers or delays, D_1 through D_N , is clocked at the spreading clock frequency, the row shift registers 64_1 through 64_4 are clocked at a lower rate that is $1/N$ times the spreading clock frequency. With this reduction in the frequency of clocking the delay stages of the row shift registers there is a concomitant reduction in power consumption.

As the digital signal samples are shifted into buffer 66, thence into row shift registers 64_1 , 64_2 , 64_3 , and 64_4 , taps at the output of each delay D_{11} through D_{N+1} provide the digital signal samples as multiplier inputs to multipliers M_{11} through M_{N+1} . Tap weight

coefficients, C_0 through C_{T-1} , such as from tap weight source 74, are provided to tap changer 76 thence by tap changer 76 as the multiplicand input to multipliers M_{11} through M_{N+1} . The product outputs O_{11} through O_{N+1} produced by the multipliers are summed in adder 70 to produce the correlation sum 72 for one sample instant.

5 In accordance with the invention, the coefficients C_0 through C_{T-1} are shifted by tap changer 76 in coordination with the digital signal samples being shifted from buffer 66 through registers D_{11} through D_{N+1} so that the appropriate product terms (outputs O_{11} through O_{N+1}) are generated to contribute to a correlation sum at each sample instant. The tap changer shifts the coefficients C_0 through C_{T-1} at the spreading clock frequency. The row
10 shift registers 64₁, 64₂, 64₃, and 64₄ shift the digital data samples at a clock rate that is $1/N$ times the spreading clock frequency. Since the coefficients in a preferred embodiment are one bit wide, the power required to shift the coefficients is relatively small by comparison to shifting all of the digital signal samples at the spreading clock frequency. Even when the coefficients have a bit width greater than one bit, there will be a power savings. For
15 example, in a CDMA system, the tap weight coefficients may be one bit wide while the digital data samples as well as the registers of the row shift registers are eight bits wide.

In order to achieve the same correlation sum as the correlation sum obtained in the straight-forward filter technique, the number of delay stages is increased to $T + N$ from T . The number of taps, multipliers, and inputs to adder 70 are also increased by N as compared
20 to the straight-forward filter technique. The tap weight coefficients, C_0 through C_{T-1} , are provided to and shifted into tap changer 76 from, for example, tap weight source 74. The spreading code tap weight coefficients are augmented with leading and trailing zeroes as illustrated in coefficient shift position 1 of Table 1 to form the augmented coefficients that are provided as the multiplicand input to multipliers M_{11} through M_{N+1} . Although Table 1
25 is prepared for the case $N = 4$, one skilled in the art can determine the tap weight coefficient shift pattern, and the multiplier associated with each tap weight coefficient in the more general case.

Coefficient Shift Position	COEFFICIENTS											
	0	0	0	C_0	C_1	C_2	...	C_{T-4}	C_{T-3}	C_{T-2}	C_{T-1}	0
1	0	0	C_0	C_1	C_2	C_3	...	C_{T-3}	C_{T-2}	C_{T-1}	0	0
2	0	C_0	C_1	C_2	C_3	C_4	...	C_{T-2}	C_{T-1}	0	0	0
3	C_0	C_1	C_2	C_3	C_4	C_5	...	C_{T-1}	0	0	0	0
4	C_0	C_1	C_2	C_3	C_4	C_5	...	C_{T-1}	0	0	0	0
Multi-plier	M_{11}	M_{21}	M_{31}	M_{41}	M_{12}	M_{22}	...	M_{4L}	M_{1L+1}	M_{2L+1}	M_{3L+1}	M_{4L+1}

TABLE 1

- 5 Once a multiplication utilizing all of the coefficients in coefficient shift position 1 of Table 1 takes place in multipliers M_{11} through $M_{N L+1}$, in addition to the product outputs O_{11} through $O_{N L+1}$ being provided as inputs to adder 70, tap changer 76 is clocked to rotate the augmented coefficients. Tap changer 76 may include a circular shift register or
- 10 combinational logic such that the augmented coefficients rotate through positions when tap changer 76 is clocked. Once tap weights are loaded into tap changer 76, the tap weights contribute to a correlation sum from the initial coefficient shift position, and tap changer 76 is clocked $N-1$ times to rotate the tap weights before the augmented coefficients are loaded from tap weight source 74 into tap changer 76 again, thereby being reset to the stored
- 15 coefficients in coefficient shift position 1.
- The effect on the augmented coefficients of tap changer 76 being clocked can be seen in the rows of Table 1. Row 1 represents the augmented coefficients as retrieved from memory. Upon clocking tap changer 76, each tap weight in row 1 of Table 1 representing
- 20 coefficient shift position 1 is circularly shifted to the left. The tap weight in the left-most column associated with multiplier M_{11} is shifted into the right-most column, to be associated with multiplier $M_{4 L+1}$ in coefficient shift position 2 of Table 1. Row 2 represents the augmented coefficients after tap changer 76 is clocked once. Row 3 represents the augmented coefficients after tap changer 76 is again clocked. Row 4 represents the augmented
- 25 coefficients after tap changer 76 is again clocked. The augmented coefficients are shifted $N-1$ times in tap changer 76, for a total number of N positions. In each position, the augmented coefficients are provided as respective multiplicands to multipliers M_{11} through $M_{N L+1}$ in the correlation process. The shift pattern represented in Table 1 is coordinated with the sequence of clocking digital signal samples into buffer 66 and the physical arrangement of multipliers

M_{11} through M_{N+1} to assure the appropriate intermediate product terms, O_{11} through O_{N+1} , are generated to produce the correlation sum 72 at each sample instant.

An alternate illustrative embodiment digital matched filter 360 is shown in Figure 3 that can be employed in a receiver and implemented in software, hardware, or some combination thereof. Elements in the embodiment illustrated in Figure 3 having reference numerals similar to reference numerals of elements in the embodiment illustrated in Figure 2 have a similar function. Buffer 366 is a serial input, parallel output buffer. In the alternate embodiment digital matched filter 360, digital signal samples are clocked into register D_1 , and shifted through the registers of buffer 366 until each of the N buffer registers has been updated. With all of the registers D_1 through D_N of buffer 366 updated with digital signal samples, the row shift registers 364₁, 364₂, 364₃, and 364₄ are clocked to shift the digital signal samples from registers D_1 through D_N of buffer 366 into respective delays of the corresponding row shift registers 364₁, 364₂, 364₃, and 364₄. In this manner, after the row shift registers are clocked $L+1$ times, all of the delays D_{11} through D_{N+1} in shift registers 364₁, 364₂, 364₃, and 364₄ are filled with valid digital signal samples. Furthermore, while each of the N registers of buffer 366, D_1 through D_N , is clocked at the spreading clock frequency, the row shift registers 364₁ through 364₄ are clocked at a lower rate that is $1/N$ times the spreading clock frequency. Filter 360 has much of the power consumption reduction of filter 60. In filter 360, there are $N - 1$ more registers of buffer 366 clocked at the spreading clock frequency than in filter 60. With this reduction in the frequency of clocking the delay stages of the row shift registers there is a concomitant reduction in power consumption.

While the illustrative embodiments of the invention have been described with respect to a CDMA communication system, the invention is not limited to being used in CDMA systems. The invention may be employed in any filter application, and may be fabricated in an integrated circuit using any known technology.

While the illustrative embodiment of the invention has been described as filling the delay buffer starting with delay D_4 , and ending with delay D_1 , the invention is not limited thereto. Other sequences of filling the buffer are within the scope of the invention.

Coordination between the sequence of filling registers of the buffer, augmenting the tap

weights with leading and trailing zeroes, and circular shifting of the augmented tap weights is necessary to produce the appropriate products to sum.

The invention has application where the bit width of tap weight coefficients is less than the bit width of the digital signal samples. Since the coefficients in a preferred
 5 embodiment are one bit wide, the power required to shift the coefficients is relatively small by comparison to shifting all of the digital signal samples at the spreading clock frequency.

It was stated above that the T taps are factored into a product of N and L , where $N \times L = T$, and N and L are any integers that divide into T , matched filter 60 is comprised of $T + N$ multiple bit delays, and that the invention can accommodate a number of taps that can not
 10 be divided into a product of two integers. As can be seen from the right column of Table 1, in the illustrated embodiment, the tap weight of multiplier M_{4L+1} is always zero. Thus, there is no contribution to the sum from multiplier M_{4L+1} , the multiplier can be eliminated, delay D_{4L+1} can be eliminated, and there is no need to provide output O_{4L+1} to adder 70. This departs from an array 62 of delays that is $N \times L + 1$. The number of delay stages in array 62 can be
 15 factored into $N \times L + 1$, with a remainder of R , where $R < N$. The R delays should be included in the shift registers such that there is no sample instant gap between the data samples in the shift registers. Where the R delays are in the array is dependent in part on the sequence of filling the buffer registers. In Figures 2 and 3, for example, if R registers were present, they would form the rightmost column of the array, and would fill in delay stages beginning from
 20 the top of the array as illustrated. An example of a digital filter in which the number of taps is not a product of two integer numbers is illustrated in Figure 4.